

# RADIO SHACK TRS-80

**CUSTOMER SERVICE BULLETIN**

**NO.**

1590-04

Description	SuperSCRIPSIT
Model	III V 01.02.02
Stock No.	260-1590
Date	OCT 5, 1984

**\*\*\*\*\*PURPOSE\*\*\*\*\***

Modifications have been developed to reduce the chances of SuperSCRIPSIT, 26-1590, "locking up" under adverse operating conditions. Modifications to the program are being accomplished by PATCHING.

**\*\*\*\*\*DISCUSSION\*\*\*\*\***

The PATCHES shown below update your software to Version 01.02.03. Please log the new version number in your Version Log as soon as you have applied the PATCHES shown under "PROCEDURE". A brief power outage or an improper exit from the program can cause a screen to show "garbage" or to lock up. This happens particularly when block action commands are attempted. The patches below are to reduce the chance of the situation happening.

**\*\*\*\*\*PROCEDURE\*\*\*\*\***

At TRSDOS READY type in the following patches for the problem.

```
PATCH SCR16/CTL (ADD=8DE8,FIND=EDB0DD7E00,CHG=CDB07C0000)
PATCH SCRIPSIT/CMD (ADD=7CB0,FIND=0000000000,CHG=E5210000CD)
PATCH SCRIPSIT/CMD (ADD=7CB5,FIND=0000000000,CHG=C165E12802)
PATCH SCRIPSIT/CMD (ADD=7CBA,FIND=0000000000,CHG=EDB0DD7E00)
PATCH SCRIPSIT/CMD (ADD=7CBF,FIND=00,CHG=C9)
```

To update the version number to 01.02.03, apply the following patch.

```
PATCH SCR17/CTL (ADD=8EC7,FIND=32,CHG=33)
```

If you need assistance, please contact your Radio Shack Computer Center, Radio Shack Computer Marketing Department, or Radio Shack Participating Dealer.