

CUSTOMER SERVICE BULLETIN

Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No.	4150-03
Description	TRSDOS
Model	Model II/16
Stock No.	26-4150 Version 4.1
Date	July 13, 1982
Page 1 of	1

Problem

In some unattended modes of operation, it is desirable to have HOST start up without prompting the operator to enable or disable the remote <BREAK> key. Listed below are some optional patches to TRSDOS 4.1 which, when applied, will allow the HOST function to start up without displaying the "Disable remote <BREAK> key (Y/N)" or requiring the operator's reply.

* * * THESE PATCHES ARE OPTIONAL! * * *

Solution

When the first patch is applied, the remote <BREAK> is automatically enabled at start up. If the second patch is applied instead of the first, HOST starts with the remote <BREAK> key disabled.

To enable the remote <BREAK> key:

```
PATCH SYSTEM/SYS R=110 B=213 F=2158F50E C=06001818
```

To disable the remote <BREAK> key:

```
PATCH SYSTEM/SYS R=110 B=213 F=2158F50E C=06011818
```

The above patches are for the 64K HOST.