

CUSTOMER SERVICE BULLETIN

Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No.	4503-10
Description	Payroll
Model	Model II
Stock No.	26-4503 Version 1.0
Date	September 23, 1980
Page 1 of	1

Problem

If an address like 2229 E 65 St is entered and no period is put after the E an OV Error occurs. This error will not occur if N, S, or W, are entered. The computer thinks it is receiving the exponential notation 229 + E65.

Solution

The problem is corrected by following the steps listed below.

1. Backup the diskette(s) and make the changes on the Backup copy of the program.
2. In BASIC load the program by typing LOAD"ADD".
3. Make the following corrections:

CHANGES (Retype the line or refer to the Edit section of the owners manual)

Old Line: 1131 IFCF>0CRIN\$<CHR\$(3)THENRETURN

New Line: 1131 IFCF>0CRIN\$<CHR\$(3)THENRETURNELSEIFI=4THENGOSUB2300:
IFIV=0THEN1130

Old Line: 1132 IFI=8ANDVAL(IN\$)>7THEN1130ELSEIFI=4THENGOSUB2300:
IFIV=0THEN1130

New Line: 1132 IFI=8THENIFVAL(IN\$)>7THEN1130

4. Type SAVE"ADD" to save the changes in the program.
5. At TRSDOS Ready, make a backup copy of the corrected diskette.