

CUSTOMER SERVICE BULLETIN

Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No. 4530-2
Description Scripsit
Model Model II
Stock No. 26-4530 Version 1.0
Date February 19, 1981
Page 1 of 1

Problem

The following patches will correct the problems you are having with wide files. The symptoms are Loss of text on printout when text appears ok on the screen and/or Print prompts appear garbled.

Solution

1. Reset your system and insert a Scripsit diskette.
2. Answer the Date prompt.
3. Press HOLD.
4. Answer the Time Prompt.
5. At TRSDOS Ready, carefully perform the following patches.

```
PATCH SCRIPSIT A=C96B F=CDCBC610FB C=CD10DB0000
PATCH SCRIPSIT A=DB10 F=0000000000000000 C=F5783DFD862C
PATCH SCRIPSIT A=DB16 F=000000000000000000 C=322F90783DFD8637
PATCH SCRIPSIT A=DB1E F=000000000000000000 C=323A90F148C3CDC6
PATCH SCRIPSIT A=C6D0 F=CDE4C6 C=C330DB
PATCH SCRIPSIT A=DB30 F=000000000000000000 C=F5C5E52B2BBE
PATCH SCRIPSIT A=DB38 F=00000000000000000000 C=C24ADB2BBE23CA4ADB
PATCH SCRIPSIT A=DB41 F=00000000000000000000 C=237E8177E1C1C353DB
PATCH SCRIPSIT A=DB4A F=00000000000000000000 C=E1C1F1CDE4C6C3D3C6
PATCH SCRIPSIT A=DB53 F=000000000000000000 C=FD352DC3ECC6
```

6. Type STARTUP and press ENTER. Scripsit will load.
7. Make a Backup of the corrected diskette.