

CUSTOMER SERVICE BULLETIN

Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

| | |
|---------------------|---------------------|
| Bulletin No. | 6105-10 |
| Description | TRSDOS 16 |
| Model | Model II/16 |
| Stock No. | 26-6105 Version 4.1 |
| Date | September 30, 1982 |
| Page 1 of | 1 |

Problem

BACKUP will make a floppy disk unusable when a single drive backup is done. This is accomplished by, BACKUP 0 0 or similar method. The correct error messages are given but the disk is modified anyway.

The patches below will still give the correct error messages, but will prevent the disk from being modified.

* * THE FOLLOWING PATCHES ARE REQUIRED! * *

Solution

1. At TRSDOS Ready, apply the following patches to correct the problem.

```
PATCH BACKUP R=1 B=65 F=41 C=4D
PATCH BACKUP R=1 B=71 F=41 C=4D
PATCH BACKUP R=1 B=77 F=41 C=4D
PATCH BACKUP R=2 B=113 F=217F321803217032CD672C21
C=216733010001CDAA2CCD952B
PATCH BACKUP R=2 B=125 F=6733010001CDAA2CCD952B
C=217F321803217032CD672C
```

2. Make a backup copy of the patched diskette.